

Modified Sine Wave

DC to AC Inverters
175 W / 300 W / 600 W



RVs, Campers, Long Haul Trucks, Boats, Cars, Mobile Office,
Service Vehicles and Emergency Back-up Power
-Innovative, compact design
-For electrical power, anywhere

Easy Solution for Small Power Needs

Compact, lightweight, and portable! The perfect inverters for middle-range power needs - powerful yet economical.

Easy to install, simply connect directly to your battery and plug your appliances into the AC outlet(s) (cables included).

Use the GP-600 for lights, drills, and blenders. Use the on/off switch to conserve power.

Go Power!™ 300 and 175 Inverters plug into a vehicle's lighter socket and are an easy solution for your small AC power needs.



Modified Sine Wave Inverters
(left to right); GP-600 W, GP-300
W and GP-175 W.

Specifications*	GP-175	GP-300	GP-600
Continuous Output Power	175 W	300 W	600 W
Surge Rating	210 W	400 W	860 W
Output Waveform	Modified Sine Wave		
Output Voltage	115 VAC RMS +5%/-10%		
Output Frequency ±1%	60 Hz	60 Hz	60 Hz
Input Voltage	10.5 - 15 VDC	10.5 - 15 VDC	10.5 - 15 VDC
Efficiency	80-90%	80-90%	80-90%
No Load Current Draw	0.2 A	0.2 A	0.2 A
Protection	Overload, Over Temp, Over Voltage, Under Voltage		
Low Battery Alarm ± 2%	10.5 V	10.5 V	10.5 V
Low Battery Shut-Down ± 2%	10 V	10 V	10 V
Operating Temperature Range	0 - 40°C / 32°F - 104°F		
Storage Temperature Range	-30°C - 70°C / -22°F - 158°F		
Cooling	Passive	Continuous fan	Continuous fan
AC Receptacles	1	2	2
Dimensions (LxWxH) mm	135 x 53 x 46	165 x 89 x 51	229 x 86 x 51
inches	5.3 x 2.1 x 1.8	6.5 x 3.5 x 2	9 x 3.4 x 2
Weight kg / lbs	0.5 / 1.1	0.84 / 1.8	2.1 / 4.6
Warranty	1 year	1 year	1 year
Inverter Install Kit	Auto Utility Adapter	Auto Utility Adapter	Spring Clamp
UPC	8-39085-00005-2	8-39085-00139-4	8-39085-00000-7

*Specifications subject to change without notice