

OPERATION AND MAINTENANCE INSTRUCTIONS FOR 46515 SERIES TWO TON PACKAGED HEAT PUMP

TABLE OF CONTENTS

ELEC. RATINGS: 115 VAC 60 Hz PHASE CIRCUIT * 10.4 RLA	I. SPECIFICATIONS					
MODEL NO. FOR OUTDOOR USE ELEC. RATINGS: 115 VAC 60 Hz I PHASE CIRCUIT *I 10.4 RLA 63.0 LRA MOTOR THERMALLY PROTECTED 3.4 FLA 1.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 0.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 19.2 AMP MIN. CIRCUIT AMPERAGE AMP 16 20 AMP AXIMUM OVERCURRENT PROTECTIVE DEVICE 32.5 OZS. MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W *12 0'-25' CONDUCTOR GAUGE (COPPER) *8 40'-63' WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT AL REMOTE ELECTRIC POWER BEFORE SERVICIN AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG	46515	-81	1			
CIRCUIT *I 10.4 RLA 63.0 LRA COMPRESSOR 1450-407 MOTOR THERMALLY PROTECTED 3.4 FLA 2.8 FLA 3.0 D. BLOWER MOTOR DATA COMPRESSOR 1450-407 MOTOR THERMALLY PROTECTED 3.4 FLA 2.8 FLA 3.0 D. BLOWER MOTOR DATA COMPRESSOR 1450-407 MOTOR THERMALLY PROTECTED LRA 63 19.2 AMP MIN. CIRCUIT AMPERAGE AMP 20 AMP AXIMUM OVERCURRENT PROTECTIVE DEVICE 32.5 OZS. R-410A CHARGE WEIGHT OZS. MINIMUM EXTERNAL STATIC PRESSURE 43 IN. W *12 0'-25' MINIMUM SUPPLY CONDUCTOR GAUGE (COPPER) UTILISER DES FILS D'ALIMENTATION EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT AL REMOTE ELECTRIC POWER BEFORE SERVICIN AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG COMPONDITI	. – – . –		•	SERIA	L NO.	
CIRCUIT #1 10.4 RLA 63.0 LRA MOTOR THERMALLY PROTECTED 3.4 FLA 1.D. BLOWER MOTOR DATA H.P. 1/3 FLA M. 2.8 FLA 0.D. BLOWER MOTOR DATA H.P. 1/3 FLA M. 2.8 FLA 19.2 AMP MIN. CIRCUIT AMPERAGE AMP 20 AMP MAXIMUM OVERCURRENT PROTECTIVE DEVICE 32.5 OZS. R-410A CHARGE WEIGHT 20 AMP MAXIMUM OVERCURRENT PROTECTIVE DEVICE 32.5 OZS. R-410A CHARGE WEIGHT CONDUCTOR GAUGE (COPPER) 10 25'-40' UTILISER DES FILS #8 40'-63' D'ALIMENTATION EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG ROOM CONDITI					TOF	
COMPRESSOR 1450-407 MOTOR THERMALLY PROTECTED 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER WOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 4.8 AD. 1/4 J.		TINGS:	II5 VAC			
1450-407 63.0 LRA 1450-407	_	n cor	MPRESSOR			
AND LEAD PROTECTED 3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 0.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 0.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 0.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA 0.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 3.19.2 AMP MIN. CIRCUIT AMPERAGE AMP 16 20 AMP PROTECTIVE DEVICE AMP 20 AMP 20 AMP PROTECTIVE DEVICE AMP 20 AMP	IU.4 RLA				RLA IU	
3.4 FLA I.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA N. 2.8 FLA O.D. 1/3 FLA	63.0 LRA			_LY	LRA 63.	
2.8 FLA O.D. BLOWER MOTOR DATA H.P. 1/3 FLA 3 19.2 AMP MIN. CIRCUIT AMPERAGE AMP 16 20 AMP PROTECTIVE DEVICE AMP 20 32.5 OZS. R-410A CHARGE WEIGHT OZS. 3 MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W *12 0'-25' MINIMUM SUPPLY O'-25' CONDUCTOR GAUGE (COPPER) 25'-40' UTILISER DES FILS *8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG				⊔ В 1/3	FLA N/A	
19.2 AMP MIN. CIRCUIT AMPERAGE AMP 16 20 AMP MAXIMUM OVERCURRENT PROTECTIVE DEVICE 32.5 OZS. R-410A CHARGE WEIGHT OZS. 3 MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W *12 0'-25' MINIMUM SUPPLY O'-25' CONDUCTOR GAUGE (COPPER) 25'-40' UTILISER DES FILS *8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG						
20 AMP PROTECTIVE DEVICE AMP 20 32.5 OZS. R-410A CHARGE WEIGHT OZS. 3 MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W *12 0'-25' MINIMUM SUPPLY 0'-25' CONDUCTOR GAUGE (COPPER) 25'-40' UTILISER DES FILS *8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG						
32.5 OZS. R-410A CHARGE WEIGHT OZS. 3 MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W #12 0'-25' MINIMUM SUPPLY 0'-25' CONDUCTOR GAUGE (COPPER) 25'-40' UTILISER DES FILS #8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG		MAXIMUM	OVERCUF	RENT		
MINIMUM EXTERNAL STATIC PRESSURE .43 IN. W #12 0'-25' MINIMUM SUPPLY 0'-25' CONDUCTOR GAUGE #10 25'-40' (COPPER) 25'-40' UTILISER DES FILS #8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG ROOM CONDITI						
CONDUCTOR GAUGE *10 25'-40' UTILISER DES FILS *8 40'-63' D'ALIMENTATION EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG						
#10 25'-40' (COPPER) 25'-40' UTILISER DES FILS #8 40'-63' D'ALIMENTATION 40'-63' EN CUIVRE WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG	#12 0'-25'				0'-25'	
WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG ROOM CONDITI	# 10 25'-40'	(COPPER)		25'-40'	
WARNING: RISK OF ELECTRIC SHOCK!!! CAN CAUSE INJURY OR DEATH. DISCONNECT ALI REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG ROOM CONDITI	*0 40' 67'				101 671	
CAUSE INJURY OR DEATH. DISCONNECT ALL REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI	+6 40 -63			ON	40 -63	
CAUSE INJURY OR DEATH. DISCONNECT ALL REMOTE ELECTRIC POWER BEFORE SERVICING AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI	WARNING: F	ISK OF F	ELECTRIC	SHOCK!	!! CAN	
AVERTISSEMENT: RISQUE DE CHOCS ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI						
ELECTRIQUES. PEUT CAUSER DES BLESSURES ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI					ERVICING	
ET MEME ENTRAINER LA MORT. COUPER LES SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI					FCCUREC	
SOURCES D'ALIMENTATION A DISTANCE AVAN LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG CONDITI						
LE DEPANNAGE. DESIGN PRESSURES HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG C U US ROOM CONDITI						
HIGH SIDE 450 PSIG / LOW SIDE 240 PSIG C ROOM CONDITI			2			
c UL ROOM		DESIG	N PRESSU	RES		
C ONDITI	111011 0101	150 00	TA / 1 A	CIDE C	40 DCT0	
CONDITI	HIGH SIDE	450 PS	IG / LOW	SIDE 24	40 PSIG	
	HIGH SIDE	450 PS	IG / LOW) "	ROOM	
RV PRODUCTS DIV. OF AIRXCEL INC., WICHITA, KS 46515	HIGH SIDE	450 PS) us	40 PSIG ROOM CONDITIO 5	

II. GENERAL INFORMATION

This packaged heat pump mounts below the floor of the vehicle. The innovative design makes it possible to maintain a smooth, free-flowing roof line for the vehicle. It also relocates all heat pump noise and condensate drainage off the roof to below the floor of the vehicle.

This heat pump contains a dual compressor system with each compressor connected to a separate refrigeration circuit. It combines the capacity of two roof mounted units into one highly efficient and compact package.

A. Air Conditioner

This heat pump operates a two stage system in cooling, running a single compressor when the air conditioning requirement is low, or with two compressors when maximum cooling is required.

The first compressor and refrigeration circuit is referred to as "1st Stage". The second compressor and refrigeration circuit is referred to as "2nd Stage". First and second stage will operate as indicated below:

1st Stage (the first compressor and refrigeration circuit) will operate when:

- 1) The thermostat is demanding cooling,
- 2) The vehicle is being powered by either shore line or the on-board generator.

2nd Stage (the second compressor and refrigeration circuit) will operate when:

- 1) The thermostat senses room temperature is 2 degrees higher than setpoint,
- 2) The vehicle has enough power.

B. Heat Pump

Heat operation always energizes both refrigeration circuits with a 30 second delay between compressor 1 start-up and compressor 2 start-up, however; only refrigeration circuit #1 operates if power is not available for circuit #2.

Thermostat operation is described in operation instructions packed with the thermostat.

The 46515 series heat pump uses a factory installed High Pressure Switch Safety Circuit. In the event of an abnormal condition (failure of fan motor, dirty condenser coil, dirty filters), the high pressure switch will prevent the compressor from continuing to run. Once the high pressure switch has tripped, this safety circuit will "Lock Out" the compressor and outdoor fan preventing them from trying to restart or run. This is a manual reset pressure switch, access shall be limited to Qualified Technicians. The manual reset push button for the pressure switch is accessed in the units electrical box and 115 volt power shall be turned off while resetting switch.

III. MAINTENANCE

One of the biggest advantages of owning a Coleman-Mach heat pump is that the maintenance needed to keep the unit in good care is minimal.

In fact, the only maintenance that must be taken care of on a regular basis is the cleaning or replacement of the units return air filters.

The manufacturer of your vehicle determines the number, size and location of the return air filters. Be sure to contact your dealer should you have any questions concerning the number of filters used and their location.

The return air filters of this system will accumulate dust and dirt more quickly than ceiling mounted systems. We recommend that the filters be checked on a weekly basis.

If the filters are not cleaned or replaced at regular intervals, they may become partially clogged with lint and dirt. A clogged filter will product a loss of air volume and may eventually cause equipment damage.

Do not operate the heat pump without return air filters. Operating the system without filters allows the lint and dirt that is normally stopped by the filter to accumulate on the cooling coil of the heat pump. This also will lead to a loss of air volume, possible equipment damage and an expensive cleaning process.

Periodically (once or twice a season), inspect the outdoor coil and brush off any accumulated residue with a soft bristled brush.

IV. WARRANTY

Let's face it. Sometimes even the best products may need service. To obtain warranty service on your Coleman-Mach air conditioner, please contact your selling dealer, or you may access our web site on the Internet at www.rvcomfort.com for answers to the most frequently asked questions and service center locations.

Airxcel, Inc. support help may be accessed by e-mail at RVPSupport@Airxcel.com.

All written correspondence should be directed to:

Airxcel, Inc. RV Products Division P.O. Box 4020 Wichita, KS 67204

IMPORTANT

- 1. Carefully read your limited two year product warranty which is packed with the product.
- 2. An optional three year extended parts only contract is available at an additional cost of \$89.95. To obtain this optional three year parts contract, fill out the application card stapled to the front of this envelope. Please mail the card and a check or money order to the address above. Applications must be made within ninety (90) days of the original purchase.
- 3. Inquiries about your Coleman-Mach air conditioner must include the model and serial numbers and the date of purchase. The model and serial numbers can be found on the unit rating plate.

Airxcel, Inc. RV Products Division P.O. Box 4020 Wichita, KS 67204